

FCC Warning

This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to Part 15 of the FCC Rules. These limitations are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into a different outlet from that the receiver is connected.
- Consult your local distributors or an experienced radio/TV technician for help.
- Shielded interface cables must be used in order to comply with emission limits.

Changes or modifications to the equipment, which are not approved by the party responsible for compliance could affect the user's authority to operate the equipment.

Copyright © 2005 All Rights Reserved.

Company has an on-going policy of upgrading its products and it may be possible that information in this document is not up-to-date. Please check with your local distributors for the latest information. No part of this document can be copied or reproduced in any form without written consent from the company.

Trademarks:

All trade names and trademarks are the properties of their respective companies.

CE Declaration of conformity

This equipment complies with the requirements relating to electromagnetic compatibility, EN 55022 class A for ITE, the essential protection requirement of Council Directive 89/336/EEC on the approximation of the laws of the Member States relating to electromagnetic compatibility.

1. Unpacking Information

Thank you for purchasing the 16-Port Fast Ethernet Switch.
Before you start, please check all the contents of this package.

The product package should include the following:

1. One 16-Port Fast Ethernet Switch
2. One power adapter
3. User's Manual
4. Screws and wall-mount plastic



2. Introduction

2.1 General Description

The device is a powerful, high-performance Fast Ethernet switch, with all 16 ports capable of 10 or 100Mbps auto-negotiation operation (NWay), which means the switch could automatically negotiate with the connected partners on the network speed and duplex mode. It is ideal for micro-segmenting large networks into smaller, connected subnets for improved performance, enabling the bandwidth demanding multimedia and imaging applications. Moreover, the 10/100Mbps auto-sensing ability provides an easy way to migrate 10Mbps to 100Mbps networks with no pain. Compared to the shared 10Mbps or 100Mbps networks, the switch delivers a dedicated 10/100Mbps connection to every attached client with no bandwidth congestion issue.

Store-and-forward switching mode promises the low latency plus eliminates all the network errors, including runt and CRC error packets. To work under full-duplex mode, transmission and reception of the frames can occur simultaneously without causing collisions as well as double the network bandwidth.

The switch is plug-n-play without any software to configure and also fully compliant with all kinds of network protocols. Moreover, the rich diagnostic LEDs on the front-panel provide the operating status of individual port and whole system.

The switch can use the following types of cabling:

- 10BASE-T Category 3, 4 or 5 UTP/STP
- 100BASE-TX Category 5 UTP/STP

Category 5 cable is preferred to use with this product in structured wiring environments. This will ensure correct operation of all ports at 10Mbps or 100Mbps.

2.2 The Front Panel



The auto-negotiation feature of the switch allows each port of the device running at one of the following four operation modes:

1. 100Mbps full-duplex
2. 100Mbps half-duplex
3. 10Mbps full-duplex
4. 10Mbps half-duplex

* Each 10/100Mbps port supports auto MDI-X capability that is the port could connect either the PC or switch without any cable adjustment.

LED definition

LED	Operation
Power	Power on (Green) Power off (off)
Link/Act	The port is connected (Green) The port is transmitting/receiving data (Blinking Green)

2.3 The Rear Panel

The rear panel of the switch is shown as below



Power Connecting

Plug the circle end of the power adapter firmly into the rear panel of the switch, and the other end into an electric service outlet then the power is ready.

3. Installing And Using the Switch

3.1 *Installing The 16-Port Fast Ethernet Switch*

Desktop Installation

Locate the switch on the desktop and place the switch on a clean, flat desk or table close to a power outlet. Plug in all network connections and the power cord, then the system is ready.

When deciding where to put the switch, you must ensure:

- It is accessible and cables can be connected easily
- Cabling is away from:
 - * Sources of electrical noise such as radios, transmitters and broadband amplifiers
 - * Power lines and fluorescent lighting fixtures.
- Water or moisture can not enter the unit
- Air flow around the unit and through the vents in the side of the case is not restricted (company recommend that you provide a minimum of 25 mm clearance)

Installing Network Cables

Station Connections with Twisted-Pair Cable

Connect each station to the switch by a twisted-pair straight cable (10BASE-T or 100BASE-T cables). Plug one RJ-45 connector into a rear-panel port of the switch, and plug the other RJ-45 connector into the station's network adapter.

Switch to Switch Connections with Twisted-Pair Cable

In making a switch to switch connection, you could use any port to connect another switch with straight or cross-over cable. As all the ports support auto MDI-X function, so the connection is independent of cable type and using a straight cable to make a switch to switch connection is allowed.



4. Product Specifications

Standard	IEEE802.3, 10BASE-T IEEE802.3u, 100BASE-TX IEEE802.3x Full Duplex operation and Flow Control
Interface	16 * RJ-45 NWay switching ports
Cable Connections	RJ-45 (10BASE-T) : Category 3,4,5 UTP/STP RJ-45 (100BASE-TX) : Category 5 UTP/STP
Network Data Rate	Auto-negotiation (10Mbps, 100Mbps)
Transmission Mode	Auto-negotiation (Full-duplex, Half-duplex)
LED indications	System Power Port Link/Activity
System Buffer Memory	160K Bytes
MAC Address Table	8K MAC entries
Filtering/Forwarding Rate	10Mbps: 14,880pps/14,880pps 100Mbps: 148,800pps/148,800pps
Emission	FCC Class A, CE, VCCI
Operating Temperature	0° ~ 40°C (32° ~ 104°F)
Operating Humidity	10% - 90%
Power Supply	External linear power adapter (12V/1A)